

HDMI 4X1 QUAD MULTI-VIEWER	Description The HDMI screen multi-viewer can display multiple image on single screen through hardware solution. Such as one projector show multiple HDMI image, computer image or video. The resolution of this device can be up to 4K@30Hz, and support many switching mode. Product Specification <table><tr><td>Switching method</td><td>panel button, IR remote</td></tr><tr><td>Resolution</td><td>up to 4K@30Hz and backward compatible</td></tr><tr><td>Display mode</td><td>Full screen, multi-viewer, left-right, one big and 3 small</td></tr><tr><td>Operation Temp</td><td>0°C to 50°C</td></tr><tr><td>Storage humidity</td><td>20% to 60% RH</td></tr><tr><td>Operation Temp</td><td>0°C to 50°C</td></tr><tr><td>Power</td><td>DC12V</td></tr><tr><td>Switch time</td><td>Seamless</td></tr></table>	Switching method	panel button, IR remote	Resolution	up to 4K@30Hz and backward compatible	Display mode	Full screen, multi-viewer, left-right, one big and 3 small	Operation Temp	0°C to 50°C	Storage humidity	20% to 60% RH	Operation Temp	0°C to 50°C	Power	DC12V	Switch time	Seamless	Panel instruction IR CH1 CH2 CH3 CH4 MODE <table><tr><td>CH 1 button</td><td>1st Channel image will be full screen and audio out to device.</td></tr><tr><td>CH2 button</td><td>2nd Channel image will be full screen and audio out to device.</td></tr><tr><td>CH3 button</td><td>3rd Channel image will be full screen and audio out to device.</td></tr><tr><td>CH4 button</td><td>4th Channel image will be full screen and audio out to device.</td></tr><tr><td>MODE button</td><td>one big and three small mode(the audio of biggest showing image will be output),quad multi-viewer(no audio), Left-right mode(no audio)</td></tr></table>	CH 1 button	1st Channel image will be full screen and audio out to device.	CH2 button	2nd Channel image will be full screen and audio out to device.	CH3 button	3rd Channel image will be full screen and audio out to device.	CH4 button	4th Channel image will be full screen and audio out to device.	MODE button	one big and three small mode(the audio of biggest showing image will be output),quad multi-viewer(no audio), Left-right mode(no audio)	IR remote instruction Full screen Back button Mode Switching button Full screen Forward button Switch 1,2,3,4 Channel to full screen Mode Switching button 5-8: unavailable MODE 5-7: unavailable CH-: Back button, Full screen mode, and switching to previous port. Eg: Currently in 2nd channel, press CH- button, will switch to 1st channel CH+: Forward button, full screen mode, and switching to next port. Eg: Currently in 3rd channel, press CH+ button, will switch to 4th channel
Switching method	panel button, IR remote																												
Resolution	up to 4K@30Hz and backward compatible																												
Display mode	Full screen, multi-viewer, left-right, one big and 3 small																												
Operation Temp	0°C to 50°C																												
Storage humidity	20% to 60% RH																												
Operation Temp	0°C to 50°C																												
Power	DC12V																												
Switch time	Seamless																												
CH 1 button	1st Channel image will be full screen and audio out to device.																												
CH2 button	2nd Channel image will be full screen and audio out to device.																												
CH3 button	3rd Channel image will be full screen and audio out to device.																												
CH4 button	4th Channel image will be full screen and audio out to device.																												
MODE button	one big and three small mode(the audio of biggest showing image will be output),quad multi-viewer(no audio), Left-right mode(no audio)																												
1	2	3																											

AUTO: MODE switching button: Press this button can switch between one big and three small mode, quad multi-viewer and Left-right mode 1/2/3/4: Switch 1/2/3/4 Channel to full screen MODE1: Quad multi-viewer.Device mute. MODE2: Left-right full mode. Press first time, 1st and 2nd Channel will be displayed. Then press again, 3rd and 4th Channel will be displayed. both mode in turn Device mute. MODE3: Left-right standard mode(not full screen). Press first time,1st and 2nd Channel will be displayed. Then press again, 3rd and 4th Channel will be displayed. both mode in turn Device mute. MODE4: One big and three small mode. The sound is synchronized with the big screen. MODE8: Turn on/off character display. Normal Mode For the convenience of customers, our company has solidified the display mode. If you need other modes, please contact our company for confirmation	1.Quad multi-viewer mode 4 HDMI equal image are displayed on one screen OUT1 A OUT3 C OUT2 B OUT4 D 2.Full screen Switch to the port you want to display in full screen OUT1 A	3.One big and three small A certain image as a background, other image three equal display, as follow. OUT1 A OUT2 B OUT3 C OUT4 D 4.Left-right mode Include: 1st and 2nd, 3rd and 4th two kinds. Show as below. OUT1 A OUT2 B Left-right full screen OUT1 A OUT2 B Left-fight no full screen	Connection diagram DC12V HDMI 4 HDMI 3 HDMI 2 HDMI 1 HDMI OUT Power port Computer DVD player Gamer Recorder Quad multi-viewer Packing list <table><tr><td>4 port video multi-viewer</td><td>1</td></tr><tr><td>Power adapter(DC12V)</td><td>1</td></tr><tr><td>IR remote controller</td><td>1</td></tr><tr><td>User manual</td><td>1</td></tr></table>	4 port video multi-viewer	1	Power adapter(DC12V)	1	IR remote controller	1	User manual	1	4	5	6	7
4 port video multi-viewer	1														
Power adapter(DC12V)	1														
IR remote controller	1														
User manual	1														

单页：75x105mm